

> RVT

Regolatore di velocità ad autotrasformatore trifase 2 A

Three-phase self-transformer speed regulator 2 A

**DESCRIZIONE**

Convertitore di tensione manuale mediante autotrasformatore con selettore a 5 posizioni. Assenza di ronzio elettrico nel motore. Adatto a motori asincroni trifase regolabili.

COSTRUZIONE

- Alimentazione 400V-3Ph-50/60Hz.
- Corrente nominale max 2 A.
- Tensione di uscita 1(90V)-2(140V)-3(180V)-4(230V)-5(400V).
- Protezione IP 54.
- Spia di funzionamento
- Contenitore in alluminio pressofuso RAL 7001 (grigio) con coperchio in materiale plastico RAL7035 (grigio chiaro).
- Peso Kg 7.5.

DESCRIPTION

Manual voltage converter by self-transformer switchover, 5 step options. Minimum magneto-acoustic noise in the motor. Suitable for three-phase asynchronous adjustable motors.

CONSTRUCTION

- Supply 400V-3Ph-50/60Hz.
- Nominal current max 2 A.
- Output voltage 1(90V)-2(140V)-3(180V)-4(230V)-5(400V).
- Protection IP 54.
- Pilot light
- Housing in die-cast aluminium RAL 7001 (grey) with cover in plastic material RAL7035 (light grey).
- Weight Kg 7,5.

DIMENSIONI E SCHEDA DI COLLEGAMENTO *Dimensions and wiring diagram*

RVT

Dimensioni in mm / Dimensions in mm

